AOT125A60L/AOTF125A60L/AOB125A60L

600V, αMOS5™ N-Channel Power Transistor

General Description

- Proprietary αMOS5™ technology
- Low $R_{DS(ON)}$
- Optimized switching parameters for better EMI performance
- Enhanced body diode for robustness and fast reverse recovery

Applications

- SMPS with PFC,Flyback and LLC topologies
- Micro inverter with DC/AC inverter topology

Product Summary

V_{DS} @ $T_{j,max}$	700V
I_{DM}	100A
$R_{DS(ON),max}$	< 0.125Ω
$Q_{g,typ}$	39nC
E_{oss} @ 400V	6.3μJ

100% UIS Tested
100% R_g Tested

Green Product



AOT125A60L



AOTF125A60L



AOB125A60L



Orderable Part Number	Package Type	Form	Minimum Order Quantity
AOTF125A60L	TO220F	Tube	1000
AOT125A60L	TO220	Tube	1000
AOB125A60L	TO263	Tape&Reel	800

Absolute Maximum Ratings T_A=25°C unless otherwise noted

Parameter		Symbol	AOT(B)125A60L	AOTF125A60L	Units
Drain-Source Voltage		V_{DS}	600		V
Gate-Source Voltage		V_{GS}	±20		V
Continuous Drain Current	T_C=25°C	I_D	28	28*	A
	T_C=100°C		18	18*	
Pulsed Drain Current [C]		I_{DM}	100		
Avalanche Current [C]	L=1mH	I_{AR}	7.9		A
Repetitive avalanche energy [C]		E_{AR}	31		mJ
Single pulsed avalanche energy [G]		E_{AS}	555		mJ
MOSFET dv/dt ruggedness		dv/dt	100		V/ns
Diode reverse recovery V_{DS}=0 to 400V,I_F<=20A,Tj=25°C		dv/dt	20		V/ns
		di/dt	500		A/us
Power Dissipation [B]	T_C=25°C	P_D	357	36	W
	Derate above 25°C		2.9	0.3	W/°C
Junction and Storage Temperature Range		T_J, T_{STG}	-55 to 150		°C
Maximum lead temperature for soldering purpose, 1/8" from case for 5 seconds		T_L	300		°C

Thermal Characteristics

Parameter	Symbol	AOT(B)125A60L	AOTF125A60L	Units
Maximum Junction-to-Ambient [A,D]	$R_{\theta JA}$	65	65	°C/W
Maximum Case-to-sink [A]	$R_{\theta CS}$	0.5	---	°C/W
Maximum Junction-to-Case	$R_{\theta JC}$	0.35	3.4	°C/W

* Drain current limited by maximum junction temperature.

Electrical Characteristics (T_J=25°C unless otherwise noted)

Symbol	Parameter	Conditions	Min	Typ	Max	Units
STATIC PARAMETERS						
BV_{DSS}	Drain-Source Breakdown Voltage	I_D=250µA, V_{GS}=0V, T_J=25°C	600			V
		I_D=250µA, V_{GS}=0V, T_J=150°C		700		
BV_{DSS} /ΔTJ	Breakdown Voltage Temperature Coefficient	I_D=250µA, V_{GS}=0V		0.51		V/ °C
I_{DSS}	Zero Gate Voltage Drain Current	V_{DS}=600V, V_{GS}=0V			1	µA
		V_{DS}=480V, T_J=125°C			10	
I_{GSS}	Gate-Body leakage current	V_{DS}=0V, V_{GS}=±20V			±100	nA
$V_{GS(th)}$	Gate Threshold Voltage	V_{DS}=5V, I_D=250µA	3.3	3.9	4.5	V
$R_{DS(ON)}$	Static Drain-Source On-Resistance	V_{GS}=10V, I_D=14A		0.108	0.125	Ω
g_{FS}	Forward Transconductance	V_{DS}=10V, I_D=14A		21		S
V_{SD}	Diode Forward Voltage	I_S=14A,V_{GS}=0V		0.86	1.2	V
I_S	Maximum Body-Diode Continuous Current				28	A
I_{SM}	Maximum Body-Diode Pulsed Current [C]				100	A
DYNAMIC PARAMETERS						
C_{iss}	Input Capacitance	V_{GS}=0V, V_{DS}=100V, f=1MHz		2993		pF
C_{oss}	Output Capacitance			85		pF
$C_{o(er)}$	Effective output capacitance, energy related [H]	V_{GS}=0V, V_{DS}=0 to 480V, f=1MHz		73		pF
$C_{o(tr)}$	Effective output capacitance, time related [I]			305		pF
C_{rss}	Reverse Transfer Capacitance	V_{GS}=0V, V_{DS}=100V, f=1MHz		0.8		pF
R_g	Gate resistance	f=1MHz		2.3		Ω
SWITCHING PARAMETERS						
Q_g	Total Gate Charge	V_{GS}=10V, V_{DS}=480V, I_D=14A		39		nC
Q_{gs}	Gate Source Charge			19		nC
Q_{gd}	Gate Drain Charge			9		nC
$t_{D(on)}$	Turn-On DelayTime	V_{GS}=10V, V_{DS}=400V, I_D=14A, R_G=5Ω		39		ns
t_r	Turn-On Rise Time			34		ns
$t_{D(off)}$	Turn-Off DelayTime			56		ns
t_f	Turn-Off Fall Time			19		ns
t_{rr}	Body Diode Reverse Recovery Time	I_F=14A, dI/dt=100A/µs, V_{DS}=400V		375		ns
I_{rm}	Peak Reverse Recovery Current			34		A
Q_{rr}	Body Diode Reverse Recovery Charge			8		µC

A. The value of $R_{\theta JA}$ is measured with the device in a still air environment with T_A =25° C.
B. The power dissipation P_D is based on $T_{J(MAX)}$=150° C, using junction-to-case thermal resistance, and is more useful in setting the upper dissipation limit for cases where additional heatsinking is used.
C. Repetitive rating, pulse width limited by junction temperature $T_{J(MAX)}$=150° C, Ratings are based on low frequency and duty cycles to keep initial T_J =25° C.
D. The $R_{\theta JA}$ is the sum of the thermal impedance from junction to case $R_{\theta JC}$ and case to ambient.
E. The static characteristics in Figures 1 to 6 are obtained using <300µs pulses, duty cycle 0.5% max.
F. These curves are based on the junction-to-case thermal impedance which is measured with the device mounted to a large heatsink, assuming a maximum junction temperature of $T_{J(MAX)}$=150° C. The SOA curve provides a single pulse rating.
G. L=60mH, I_{AS}=4.3A, R_G=25Ω, Starting T_J=25° C.
H. $C_{o(er)}$ is a fixed capacitance that gives the same stored energy as C_{oss} while V_{DS} is rising from 0 to 80% $V_{(BR)DSS}$.
I. $C_{o(tr)}$ is a fixed capacitance that gives the same charging time as C_{oss} while V_{DS} is rising from 0 to 80% $V_{(BR)DSS}$.

TYPICAL ELECTRICAL AND THERMAL CHARACTERISTICS



Figure 1: On-Region Characteristics



Figure 2: Transfer Characteristics



Figure 3: On-Resistance vs. Drain Current and Gate Voltage



Figure 4: On-Resistance vs. Junction Temperature



Figure 5: Break Down vs. Junction Temparature



Figure 6: Body-Diode Characteristics

TYPICAL ELECTRICAL AND THERMAL CHARACTERISTICS



Figure 7: Gate-Charge Characteristics



Figure 8: Capacitance Characteristics



Figure 9: Coss stored Energy



Figure 10: Current De-rating (Note F)



Figure 11: Maximum Forward Biased Safe Operating Area for AOT(B)125A60L (Note F)



Figure 12: Maximum Forward Biased Safe Operating Area for AOTF125A60L (Note F)

TYPICAL ELECTRICAL AND THERMAL CHARACTERISTICS



Figure 13: Normalized Maximum Transient Thermal Impedance for AOT(B)125A60L (Note F)



Figure 14: Normalized Maximum Transient Thermal Impedance for AOTF125A60L (Note F)

Gate Charge Test Circuit & Waveform



Resistive Switching Test Circuit & Waveforms



Unclamped Inductive Switching (UIS) Test Circuit & Waveforms



Diode Recovery Test Circuit & Waveforms